

DuraSpin[™] Cordless Screw Driver Model DS200-14v



DuraSpin, the collated screw fastening system from SENCO®, is designed to maximize efficiency in a wide variety of screw-fastening applications. Engineered for comfort and convenience, the DS200-14v cordless screw driver drives 1" to 2" screws.



Tool Specifications:

Voltage: 14.4 volts

Battery Ampacity: 1700 mAh

RPM: 2300 rev/min Weight: 4.9 lbs. (2.2 kg) Height: 10 inches (254 mm) Length: 13.8 inches (350 mm) Width: 2.8 inches (70 mm) Recharge Time: 1 hour

Screw Drives/Charge: see chart on reverse side

Fastener Capacity: 50 screws (one strip)

Torque Delivered: 37 in-lbs Generated Noise: 74 dBA Vibration: less than 2.5m/sec²

Applications:

For drywallers and remodelers, DuraSpin is the ideal tool for drywall (to wood or steel studs), floor sheathing, and underlayment.

Features and Benefits:

- 14.4 volt battery provides the optimum balance of power, weight and run-time across the full range of screws
- 2,300 RPM high-torque motor drives screws without bogging down
- Patented clutch design means long-lasting durability
- One-hour charger and extra battery ensures a backup battery with a full charge
- Easy depth-of-drive adjustment regulates the precise amount of countersink
- Easy bit change from phillips to square
- Wide range of collated screws to speed production
- Belt hook DuraSpin goes where you go
- One full year warranty

Fastener Specifications:

Screw Lengths: 1" (25 mm) to 2" (50 mm)

Screw Diameters: #6, #7, #8

Application:	Drywall to Wood	Drywall to Light Gauge Steel	Drywall to Heavy Gauge Steel	Wood to Wood
Drive/Head:	#2 Phillips Bugle	#2 Phillips Bugle	#2 Phillips Bugle	#2 Square Flat
Thread:	Coarse	Fine	Fine	Coarse 2/3 with Wax
Point:	Sharp	Sharp	Drill	Sharp
Finish:	Grey Phosphate	Grey Phosphate	Clear Zinc	Yellow Zinc
Screw:	#6 X 1½" #6 X 1½" #7 X 2°	#6X11/4"	#6 X 11/4."	#8 X 11/2 #8 X 11/2



DuraSpin[™] Cordless Screw Driver Model DS200-14v



Provides full charge in one hour—increases productivity and decreases downtime

Typical Applications and Screws Used	Average Number of Screws Driven Per Charge	Screw Reorder Code			
Drywall to Wood					
#6 X 1 ¹ /4" Screws	650	06A125P			
#6 X 15/8" Screws	450	06A162P			
#7 X 2" Screws	300	07A200P			
Drywall to Light Gauge Steel					
#6 X 11/4" Screws	700 (25 GAUGE) 600 (20 GAUGE)	06B125P			
Drywall to Heavy Gauge Steel					
#6 X 1 ¹ /4" Screws	300 (18 GAUGE)	06C125C			
Subfloor to Wood					
#6 X 1 ⁵ /8" Screws	350	06A162P			
#8 X 1 ¹ / ₂ " Screws	250	08F150Y			
#8 X 1 ³ /4" Screws	200	08F175Y			

These are representative averages. Your results may vary based on specific work conditions.

Each tool comes complete with:
Two 14.4 volt batteries,
one-hour battery charger,
2 spare drive bits, and a
rugged carrying case.

For additional information on how Senco fastening systems will save you time, reduce costs and increase quality, call your nearest Authorized Senco Dealer or Distributor listed in the Yellow Pages under "Staples," or call our toll-free Action Line: 1-800-543-4596.

www.senco.com

Free Manuals Download Website

http://myh66.com

http://usermanuals.us

http://www.somanuals.com

http://www.4manuals.cc

http://www.manual-lib.com

http://www.404manual.com

http://www.luxmanual.com

http://aubethermostatmanual.com

Golf course search by state

http://golfingnear.com

Email search by domain

http://emailbydomain.com

Auto manuals search

http://auto.somanuals.com

TV manuals search

http://tv.somanuals.com